

Produkt 530382



530382 Aktiv hållare med cigg-kontakt Med laddningen integrerad i hållaren. För Li-Ion eller Li-Poly batterier.

Använder du en Komradio varje dag i ditt arbete? Då kommer en aktiv hållare från Brodit att göra dina dagar mycket enklare! Genom att ha enheten i en aktiv hållare, kommer du alltid att ha den inom bekvämt räckhåll när du kör mellan jobben.

Den aktiva hållaren har en unik slimmad design med laddningen integrerat i hållare och en lysdiod som indikerar laddning pågår, indikatorn ändras från rött till grönt när den är fulladdad. Monteras på ProClip Monteringsplattform.

EAN: 7320285303829

Artikel nr 530382 passar till:

ICOM IC-F70

ICOM IC-F9011T

MONTERINGSANVISNING

1.

2.

IMAGE
MISSING

IMAGE
MISSING

3.

4.

IMAGE
MISSING

IMAGE
MISSING

Charging Specifications:

Battery Chemistry: Li-ion or Li-Poly batteries

Input Voltage: 11-30 V

Charging Voltage: 8.4 V

Timer for Max. Charging Time: Automatic, stops at 8.4 V

Max. Charging Time: 2-3 hours depending on battery capacity

Rapid Charge: 1,2 A +/- 5%

Trickle Charge: 0 to 50 mA

LED Charging Indicator: LED Red to Green indicator

Temperature Control: Controlled by battery

Operating Temperature: -40 to 50 °C (can be restricted by battery chemistry)

RoHS Compliant: Yes

Input Transient Protected: Withstands +150V & -450V. A 2,5A fuse is mounted on the incoming supply.

Output Short Circuit Protected: The charger will supply a maximum current of 1,2 A which protects both the charger and the connected equipment. The current limit is set to standards of the producer and shall not be higher.